



A1446 Addressable Loop Interfaces



**Sounder Controller Interface Module
For Apollo Protocol Analogue Addressable Control Panels**



Key Features

- ◆ Ideal for use with all Control Equipment's Apollo protocol analogue addressable control panels
- ◆ 3 inputs, prioritised in the protocol
- ◆ 1 two-stage programmable alarm circuit rated 1 Amp @ 24V DC
- ◆ 1 programmable relay rated 1 Amp @ 24V DC
- ◆ Loop terminals with test probe locator
- ◆ Normally Open or Normally Closed input selection
- ◆ Selectable type code options
- ◆ The A1447 Zone Module Adaptor board fits to the motherboard to change two of the inputs to fully monitored circuits
- ◆ The highest quality of design, componentry and manufacture for outstanding durability
- ◆ Uses the latest manufacturing technology to ensure consistency and reliability of product supply

From the UK's leading control panel manufacturer



Introduction

The Control Equipment range of loop interfaces are designed to allow remote monitoring of 3 voltage free contacts via the loop and communicate their status to the panel using analogue values.

The A1446 Sounder Controller Interface has a single change-over relay and fully-monitored sounder output circuit which can operate in pulsed or continuous mode. It requires a 24V DC supply.

The A1447 Zone Monitor Unit can be used with the A1446 to provide remote switch monitoring with fault detection.

Technical Specifications

Supply Voltage:	17-25V loop derived & from separate PSE
Quiescent Current:	1.0mA loop derived + 0.5mA per active output
Input Terminals:	Loop connections, 3 inputs for voltage-free contacts, external power supply
Analogue Values:	64 - Input 1 operated 48 - Input 2 operated 4 - Fault Input operated or local fault 16 - Quiescent condition
Local Power Supply Current:	Quiescent condition: 10mA Full alarm load: 800mA
Additional Input:	Synchronised input
Outputs:	Change-over relay rated 1 Amp @ 24V DC One monitored alarm circuit rated 750mA Synchronised output

Part Numbers

2500/238	A1446 Sounder Controller Interface
2500/248	A1446 Sounder Controller Interface Boxed
2500/254	A1446 Relay Interface & PSE Boxed

From the UK's leading control panel manufacturer

Control Equipment Ltd, Hillcrest Business Park, Cinderbank, Dudley, West Midlands, DY2 9AP, United Kingdom

Phone: +44 (0)1384 458651 Fax: +44 (0)1384 458972
Email: celsales@controlequipment.co.uk Website: www.controlequipment.com

a1446SL/rev0/10.01